



### C.8.2.6.

#### Sensitive PD detection on high voltage XLPE cable lines using field coupling sensors

HEINRICH R., Schaffner EMC-Systems GmbH, Germany  
RETHMEIER K., KALKNER W. Technical University Berlin, Germany  
PLATH R., IPH, High Voltage Lab., Germany  
WEISSENBERG W., BRUGG KABEL AG

#### **Résumé:**

Avec des essais en laboratoire et les essais après-  
pose, les avantages et désavantages de différents  
capteurs de décharges partielles aux accessoires des  
câbles PR de haute et très haute tension ainsi que  
des méthodes et instruments de mesure sont discutés  
et comparés.

#### **Abstract**

Based on experiences of laboratory and on-site  
after laying tests the advantages and limits of  
different sensors for PD detection at high  
voltage and extremely high voltage XLPE cable  
accessories as well as suitable methods and  
measurement devices for evaluation of the  
measured signals are discussed and compared.

## 1 Introduction

Partial discharge (PD) measurements on  
electrical components and complete systems  
gain more and more in importance. Thereby, it  
is of increasing interest to carry out sensitive  
PD measurements not only in (expensive), well  
shielded laboratories, but also under noisy  
conditions, e.g. unshielded laboratories for  
routine, type and development testing.  
Particularly with regard to on-site testing of  
high voltage extruded cable systems, sensitive  
PD measurements deliver high reliability [1].

The suitability of PD measurements depends  
essentially on the actual noise level on site and  
on the achievable sensitivity. Due to the strong  
damping of PD impulses at their propagation  
along the cable the conventional PD detection  
at the cable end leads strictly to a strong  
decrease in PD sensitivity with increasing  
cable length. However, the cables already  
have been PD-tested during their routine test  
at the manufacturer, so cables should be free  
of PD faults when leaving the factory. Cable  
damages due to transport or laying are usually  
discovered by sheath testing. So, on-site PD  
measurements on cable systems can focus on  
cable accessories [2, 3]. Of course,  
components of prefabricated accessories were

already PD pre-tested at the manufacturer's  
lab, but mounting the accessories on site  
leaves a certain risk for remaining faults, which  
might lead to breakdown later-on in service.  
To achieve maximum PD sensitivity on site,  
PD sensors directly at resp. inside the  
accessories are used. Different kinds of  
unconventional PD coupling methods basing  
on e.g. capacitive or inductive sensors led to  
increased PD sensitivity at the accessories  
(joints) compared to conventional PD detection  
at the cable end. Nevertheless, most of these  
methods hardly reach target PD sensitivity of a  
few pC under noisy on-site conditions [4].

However, a considerable improvement could  
be reached by the use of directional coupler  
sensors. In principle, directional coupler  
sensors give a clear and reliable distinction  
between PD caused inside a joint and external  
(noise) signals from the left or from the right of  
the joint. The very high measuring sensitivity of  
 $\leq 1\text{pC}$  becomes also possible under extreme  
electromagnetic disturbances on site (or also  
e.g. in a completely unshielded laboratory) [5,  
6, 7]. This is an essential advantage of the  
directional coupler PD measuring technique  
compared to any other type of sensor without  
inherent directivity (e.g. capacitive sensors,  
Rogowski coils). In addition, the high  
frequency range of the directional coupler