# A Fundamental Study on Electrical Properties of Reactor-made Thermoplastic Olefin for the Eco-friendly Power Cable. (case study of on-going research)

**Prof. LEE, JUNE-HO** 

leejh@hoseo.edu

**HOSEO UNIV., KOREA** 



#### **Backgrounds**


# XLPE Non-cross linked polymer Thermoplastic in electrical and mechanical Difficult to recycle Thermosetting Easy to recycle Eco-friendly

#### In this work

- Thermoplastic olefin samples containing the polypropylene(PP) and ethylenepropylene copolymer which were made in the reactor simultaneously were prepared to test.
  - AC Breakdown (ACBD) Test
  - Accelerated Life Test (ALT)
  - Water Tree Test
  - Space Charge Distribution Test

#### **Samples**

The process of reactor-made thermoplastic olefin(RTPO) can make the size of EPR smaller and control the size distributions of EPRs effectively.




SEM of a sample tested

		Thickness			
	Samples	ACBD	ALT	Water Tree	Space Charge
	XLPE (reference)	210+20[]		950±10[]	200±10[]
\	Eco-friendly polymer Group N2				ουυ±1υ[μπ]
	Eco-friendly polymer Group N2	210±20[μm]		850±10[μm]	800±10[μι




**\*** McKeown electrode used

#### McKeown electrode







<Structure of McKeown electrode>

<Actual picture of McKeown electrode>

#### **Electrodes for breakdown test**

- McKeown electrode (feasibility and easiness for application)
- > Molded electrode
- > Recess electrode

#### **Advantages of McKeown electrode**


- ➤ Improve the accuracy of the sample thickness measurement.
- Receive only little effect by interface and surrounding mediums.
- > Calculate the exact breakdown field.
- > Remove air bubbles in the epoxy into a vacuum treatment.



#### **AC Breakdown test**




#### **ACBD** test



#### Results of AC breakdown test

#### **Group N2 vs. XLPE**



sample		
N21	6.2	298
N22	6.5	338
N23	6.7	229
N24	6.5	340
N25	6.7	349
XLPE	11.2	364

 $\eta$ : scale parameter


- Characteristics electrical field

 $\beta$ : shape parameter

- Slope of the line




#### Results of AC breakdown test




### Accelerated water treeing test



#### Water Tree test cell




<One side of the sample>



<The opposite side of the sample>

Jicable HVDC'16 WORKSHOP



Sample	XLPE Group N1 Group N2	Time	300[hr]
Aqueous solution	NaCl	Pretreatment	20[torr]
E-field	10[kV/mm]	Frequency	400[Hz]

case of 400[Hz], the accelerating factor of 6.67 than 60[Hz].

Workshop Jicable HVDC'16, Friday, August 26, 2016 - Paris - France


#### Results of water tree test (XLPE)




< Water Tree degraded XLPE >

Workshop Jicable HVDC'16, Friday, August 26, 2016 - Paris - France

#### Top view of water treed samples (Group N2)




#### Cross section of water treed samples (Group N2)







< N22 >



In case of N23, the sample cross section was so opaque that we could not the check



#### **Group N2**


Water Tree was not observed on the cross section



### Accerelated Life Test (ALT)




#### **Accelerated Life Test**




Workshop Jicable HVDC'16, Friday, August 26, 2016 - Paris - France

#### **Results of the ALT**

#### At 22kVrms stress









#### $\eta$ : Characteristics life time

#### **Results of the ALT**


#### At 26kVrms stress







#### **Results of the ALT**




# **Space Charge Distributions** (by PEA method)




#### Results of space charge distribution

#### DC E-field profile for space charge test



Workshop Jicable HVDC'16, Friday, August 26, 2016 - Paris - France

#### Results of space charge distribution



- ➤ Right after grounding, the space charge distributions from all the samples of group N2 except N23 was smaller than that of XLPE.
- > After 12 hours grounding, the accumulated space charge in group N2 disappeared rapidly in contrast to the XLPE.
- > Samples in the group N2 showed better space charge distribution properties than that of XLPE.



#### **Summaries and Questions**

#### Based on basic measurements of electrical properties

#### For the reliable application of recyclable polymers to the power cable

Deeper understanding based on the fundamental research is needed

#### Mechanism of treeing initiation and growth(water treeing/ electrical treeing)

- Why the water treeing is not observed in recyclable polymers?
- Staining method? Too fine channel? Water treeing retarded?

The <u>ALT</u> might be a second-best way to give a statistical results to evaluate the long-term performance of new materials

#### What makes the difference of spacecharge among the samples?

- Size of copolymers/ size distributions/ catalysis of process
- Heat treatment/ Anti-oxidants/ etc.



## Thanks for your kind attention